Changing User Codes

With the **system disarmed** you are ready to begin.

Type [*****][**5**][**master code**] , *this will put you in the user programing mode.*

To add a new user such as user #14:
Type [**1**][**4**]
Type [*] to select access code
            , *then type* [**user 14's 4 digit code**],
Type [**#**] *to exit one level*

To change a user such as user #14 :
Type **[1][4]**
Type [*] to select access code
            , *then type* [**user 14's new 4 digit code**],
Type [**#**] *to exit one level*

To delete a user such as user #14 :
Type [**1**][**4**]
Type [*] to select access code
            , *then type* [***]** *to delete that user*,
Type [**#**] *to exit one level*

Changing User Label

With the **system disarmed** you are ready to begin.

Type [*][5][**master code**] , *this will put you in the user programing mode.*

To add a new user Label such as user #14:
Type [1][4]
Type [>] to move to user label
Type [*] to select user label
       , *then type* user name following chart below
to save Type [*] , *then* [<] , *then* [*] *to save*

To change a user label such as user #14 :
Type [1][4]
Type [>] to move to user label
Type [*] to select user label
       , *then type* user name following chart below
to save Type [*] , *then* [<] , *then* [*] *to save*

To delete a user label such as user #14 :
Type [1][4]
Type [>] to move to user label
Type [*] to select user label
       , *then type* [0] to erase users name
to save Type [*] , *then* [<] , *then* [*] *to save*

Press	To Select/Display
[*]	[SELECT]
[#]	[ESCAPE] (note: exits without saving label)
[0]	[SPACE]
[1]	[A], [B], [C], [1]
[2]	[D], [E], [F], [2]
[3]	[G], [H], [I], [3]
[4]	[J], [K], [L], [4]
[5]	[M], [N], [O], [5]
[6]	[P], [Q], [R], [6]
[7]	[S], [T], [U], [7]
[8]	[V], [W], [X], [8]
[9]	[Y], [Z], [9], [0]